

Item name	Xlink
Ordering code	RC02-W
Item code	Y57K-F1
Date	10-SEPT-2025

## Xlink



### Description

Xlink is a wireless, long-range, Casambi-enabled, user interface that brings huge flexibility to interior design as furniture can be replaced and walls can be rebuilt without having to take the wiring of switches or switch placement into account. The switch can be kept wherever the user needs it and it gives direct access to all the important Casambi lighting control functionalities.

### BASIC FUNCTIONS:-

The Preset buttons of Xlink can be configured via the casambi app. A light indicates the selected preset.

#### Dim up, Dim down:

- Smooth dimming of last chosen preset

#### Multipurpose buttons:

- Change of color temperature in steps of 25 Kelvin
- Change of the indirect/direct ratio

#### Preset buttons:

- Individual luminaire control
- Group control
- Control of all luminaires
- Recall scenes
- Recall animations

### Technical Information

Input Voltage	3VDC
Battery Type	AAA (2 no.)
Operating frequencies	2.402 to 2.480 Ghz
Max. output Power	+8 dBm
Operating temp	0°C to +40°C
Storage temp	-25°C to +70°C
Max. relative humidity	0 to 80%, non-cond.
Dimensions	Remote control: Ø57x h 19 mm Base : 85x85x11 mm
Weight	Remote control: 50g, with base: 70g
Degree of protection	IP20 (indoor use only)



CASAMBI  
xlink



[www.lbd.lighting](http://www.lbd.lighting)

Item name	Xlink
Ordering code	RC02-W
Item code	Y57K-F1
Date	10-SEPT-2025

## SMART FUNCTIONS:-

### Dimming

- **Hold the Dim down or Dim up button:** Smooth dimming of last chosen preset, cycle takes 5 seconds
- **Press the Dim down button:** Chosen preset goes to 0%
- **Press the Dim up button:** Chosen preset goes to 100%

### Preset Buttons

- **Press:** The chosen preset (luminaire control, group control, all luminaires, scene recall or animation recall) will turn on
- **Press again:** The chosen preset (luminaire control, group control, all luminaires, scene recall or animation recall) will turn off

### Color Temperature

- **Hold the Multipurpose button:** Changes color temperature smoothly, cycle takes 5 seconds
- **Press the upper Multipurpose button:** Changes to the warmest color temperature
- **Press the lower Multipurpose button:** Changes to the coldest color temperature

### Turn Off

- **Press the Dim down and Dim up button for more than 1 second:** Turns all luminaires off in selected network

### Indirect/Direct Ratio\*

- **Hold the upper Multipurpose button:** Dims up smoothly the indirect lighting, cycle takes 5 seconds
- **Hold the lower Multipurpose button:** Dims up smoothly the direct lighting, cycle takes 5 seconds
- **Press the upper Multipurpose button:** The indirect part goes to max level
- **Press the lower Multipurpose button:** The direct part goes to max level

\*sum of indirect/direct in all cases 100%

**CASAMBI**  
*xlink*

We reserve the right to change specifications without prior notification.